

Tabela montażowa – obwód kier. „Centrum”

Słup nr		ST	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	21	19	20	Razem
Typ			K	KK	K	K	N	P	P	P	P	P	P	K	K	P	P	P	P	PK	K	N	K	
Żerdzie	E-9/2,5		1	1	1	1	1							1	1					1	1	1	1	11
	ŻN-9							1	1	1	1	1	1			1	1	1	1					10
Przęsło	Typ przewodów	YAKXS	AsXS _n	AsXS _n	YAKXS	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	YAKXS	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	AsXS _n	180 623(600)
	Przekrój (mm ²)	4x25	2x25	2x25	4x25	2x25	2x25	2x25	2x25	2x25	2x25	2x25	2x25	2x25	4x25	2x25	2x25	2x25	2x25	2x25	2x25	2x25	2x25	
	Długość (m)	70	16	35	55	31	31	35	35	35	35	35	35	35	55	35	35	35	35	35	30	36	36	
	Napężenie (MPa)		30	30		30	30	30	30	30	30	30	30	30		30	30	30	30	30	30	30	30	
Ośłona (m)	SV 60	1,5																						1,5
Ustój	UB-1							1	1	1	1	1	1			1	1	1	1					10
	UB-2		1	1	1	1	1							1	1					1	1	1	1	11
Hak	SOT 21.16		1	2	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	2	1	1	1	23
Uchwyt odc.	SO 80.235S		1	2	1	1								1	1					1	1		1	10
Uchwyt przel.	SO 270						1	1	1	1	1	1	1			1	1	1	1	1		1		13
Uchwyt dyst.	SO 79.6		6		6	6								6	6						1		1	32
Ogranicznik przepięć	30.166		2		2	2								2	2								2	12
Bednarka (m)	FeZn 30x4		20		20	20								20	20								20	120
Wysięgnik	WR-1/10		1	1		1		1		1		1		1		1		1		1	1		1	12
Oprawa	LED wg opisu		1	1		1		1		1		1		1		1		1		1	1		1	12
Oprawa bezp.	SV 19.25		1	1		1		1		1		1		1		1		1		1	1		1	12
Zacisk	SL 12.05		2	2		2		2		2		2		2		2		2		2	2		2	24
Wkładka	Wts 6A		1	1		1		1		1		1		1		1		1		1	1		1	12
Przewód (m)	YDY 2x2,5		3	3		3		3		3		3		3		3		3		3	3		3	36